

FULBANK 2000

Datasheet

FULBAT™

BATTERY CHARGERS



AUTOMATIC SMART BATTERY BANK CHARGER & MAINTAINER

SPECIFICATIONS

Voltage
6/12V

Current
3x2Ah

Stages
4

Battery
4 > 40 Ah

With 3 channels available, the FULBANK 2000 diagnoses, charges and maintains batteries from 4Ah to 40Ah (120Ah in maintenance). This 6V-12V bank charger is compatible with lead-acid (Gel, AGM, MF, Dry, Ca/Ca, Wet) and Lithium (LiFePO4) batteries.

Delivered with 3 battery clamps and 3 fused connection sets, this bank battery charger has been designed to charge up to 3 batteries at the same time (with different chemistries, capacities or types). Reverse polarity, overcharge and overheat protections ensure maximum security when using this charger.

FEATURES

- Charges and maintains 3 batteries with different voltage and chemistries at once
- 2A per bank with capacity up to 40Ah (120Ah in maintenance)
- 100% Automatic
- For all batteries: GEL, AGM, MF, DRY, Ca/Ca & LiFePO4
- Easy to read LED display
- Full protected against short circuit, wrong connections, overcharge and overheat
- Splash and dust proof (IP65)
- Delivered with 3 clamps and 3 fused connection set

BOX CONTENT

- Fulbank 2000
- 3 clamps set
- 3 fused connection set



TECHNOLOGY COMPATIBILITIES

GEL

AGM

MF

DRY

WET

LiFePO4

CHARGING FEATURES

CHARGING FEATURES FULBANK 2000 - 4 STAGES

	BATTERY CHECK	BULK CHARGE	ABSORPTION	FLOAT
Voltage (V)	6V / 12V detection	Increases to set voltage	Stabilizes at set voltage	Stabilizes at 100% charge
Current (A)	0A	Maximum current	Decreases to maintain charge	0A
	6V / 12V detection	Reduces charging time by delivering maximum charge to set voltage.	Ensures a full charge to the battery without overcharging.	Float charge maintains the battery at 100% charge.

